

NCK-N-4-3

N Connectors, DC~4GHz, 3-in-1

Features:

* High Precision

Applications:

* Calibration
* Laboratory Test



Description

With the components in the kit you can make error-corrected measurements of devices supplied with N connectors from DC to 4 GHz.

Components

| Part Number | Description | Frequency | Impedance | VSWR | Phase Accuracy | Inner Conductor | Outer Conductor | Size |
|----------------------------|------------------------------|-----------|-----------|--------|----------------|------------------------------|----------------------------|------------|
| | | (GHz) | (Ω) | (Max.) | (°, Max.) | | | (mm) |
| Opens | N open | DC~4 | 50 | - | ±0.6 | Gold plated beryllium copper | Passivated stainless steel | - |
| Shorts | N short | | | - | ±0.6 | | | - |
| Coaxial Terminations | N termination | | | 1.025 | - | | | - |
| Connect Joint ¹ | | | | - | - | Aluminium oxide | | - |
| NANNC-MM ² | N male to N male adapter | | | 1.05 | - | Gold plated beryllium copper | Passivated stainless steel | - |
| NANNC-FF-3 ² | N female to N female adapter | | | | | | | - |
| Storage Box | | - | - | - | - | Aluminium | | 160*130*65 |

[1]The connector connects the Opens, Shorts and Coaxial Terminations

[2]Equal phase adapter

How To Order

NCK-N-4-3-M 3-in-1, male, including open, short and termination.

NCK-N-4-3-F 3-in-1, female, including open, short and termination.

To order a single component, specify the part number in the first column.