

## NCK-N-6-3

N Connectors, DC~6GHz, 3-in-1

### Features:

\* High Precision

### Applications:

\* Calibration  
\* Laboratory Test



### Description

With the components in these kits you can make error-corrected measurements of devices supplied with N connectors from DC to 6 GHz.

### Components

Part Number	Description	Frequency	Impedance	VSWR	Phase Accuracy	Inner Conductor	Outer Conductor	Size
		(GHz)	(Ω)	(Max.)	(°, Max.)			(mm)
Opens	N open	DC~6	50	-	±0.6	Gold plated beryllium copper	Passivated stainless steel	-
Shorts	N short			-	±0.6			-
Coaxial Terminations	N termination			1.032	-			-
Connect Joint <sup>1</sup>				-	-	Aluminium oxide		
NANNC-MM <sup>2</sup>	N male to N male adapter			1.05	-	Gold plated beryllium copper	Passivated stainless steel	-
NANNC-FF <sup>2</sup>	N female to N female adapter							-
Storage Box		-	-	-	-	Aluminium		160*130*65

[1] The Combination connects the Opens, Shorts and Coaxial Terminations

[2] Equal phase adapter

### How To Order

**NCK-N-6-3-M** 3-in-1, male, including open, short and termination.

**NCK-N-6-3-F** 3-in-1, female, including open, short and termination.

To order a single component, specify the part number in the first column.