

## NCK-V-67

### 1.85mm Connectors, DC~67GHz

Features:  
\* High Precision

Applications:  
\* Calibration  
\* Laboratory Test



### Description

With the components in the kit you can make error-corrected measurements of devices supplied with 1.85mm connectors from DC to 67 GHz.

### Components

| Part Number  | Description                               | Frequency                   | VSWR   | Phase Accuracy | Size                  |
|--------------|---|-----------------------------|--------|----------------|-----------------------|
|              |   | (GHz)                       | (Max.) | ( °, Max.)     | (mm)                  |
| NOVC-M-67    | 1.85mm male open                          | DC-20<br>20-67              | -      | ±2.5           | -                     |
| NOVC-F-67    | 1.85mm female open                        |                             |        | ±5.0           | -                     |
| NSVC-M-67    | 1.85mm male short                         | DC-67                       | -      | ±2.0           | -                     |
| NSVC-F-67    | 1.85mm female short                       |                             |        |                | -                     |
| NCT-V-C-M-67 | 1.85mm male termination                   | DC-67                       | 1.15   | -              | -                     |
| NCT-V-C-F-67 | 1.85mm female termination                 |                             |        |                | -                     |
| NW-V1-CK     | 1.85mm torque wrench                      | -                           | -      | -              | 8.1<br>(Opening size) |
| NAVVC-MM*    | 1.85mm male to<br>1.85mm male adapter     | DC-26.5<br>26.5-40<br>40-67 | 1.15   | -              | -                     |
| NAVVC-MF*    | 1.85mm male to<br>1.85mm female adapter   |                             | 1.22   |                | -                     |
| NAVVC-FF*    | 1.85mm female to<br>1.85mm female adapter |                             | 1.33   |                | -                     |
| Storage Box  |   | -                           | -      | -              | -                     |

“\*” Equal phase adapter

### How To Order

**NCK-V-67-10** All the 10 components in one box.