

# Waveguide to Coax Adapters

# NWCA -- O-NF-R WR-90 to N female, Right angle

Features: \* Low VSWR

Applications: \* Wireless

\* Transmitter \* Laboratory Test

\* Radar

## **Electrical**

Frequency:  $8.2\sim12.5 \text{GHz}$  VSWR: 1.2 max. Impedance:  $50\Omega$ 

#### Mechanical

Length: 40mm

1.575in

RF Connectors: N Female


Interface: WR-90 Flange: FBP100 Material: Aluminium

## **How To Order**

NWCA-90-NF-R

Customization is available upon request.

## **Outline Drawings**



Unit: mm [in]

Tolerance: ±0.2mm [±0.008in]